

Due: **Friday, February 23 at 1:00 pm.**

Submission: You may submit the assignment either by bringing a paper copy to class, or by sending an email to **submit105@cs.grinnell.edu**.

Lecture Component

1. For this problem, suppose we have a computer system that stores (positive and negative) integers in “Two’s Complement” notation. However, we will use only 8 bits for each number, instead of the more common 16 or 32 bits.

(a) Convert the following two’s complement number to base 10: 00101101

(b) Convert the following two’s complement number to base 10: 11100110

Hint: You may want to convert to the corresponding positive binary number first.

(c) Complete the following addition problem *in binary*.

Hint: You may want to check your work by converting your result to base 10.

```
00101101
+11100110
-----
```

2. The following sequence of numbers is a message, encoded in ASCII format. (Each number is the decimal code for a given text character.) Decode the message.

73 115 110 39 116 32 67 83 32 102 117 110 63

Laboratory Component:

Please submit written responses to **questions 3-6, 13, 15-16, and 22-24** of the laboratory on Image Processing held Friday, February 16.